

((())) ELATEC RFID		TWN3							
with Antenna →		Mifare	Mifare NFC, Mini Reader	Multi ISO	iClass	Legic	Legic NFC	HID Prox	Multi125
without Antenna →		Nano Modul		Nano Modul		Nano Modul			
13.56 MHz	ISO14443A								
	MIFARE Classic	✓	✓	✓		✓ 1)	✓ 1)		
	MIFARE Mini	✓	✓	✓		✓ 1)	✓ 1)		
	MIFARE DESFireEV1	✓ 1)	✓	✓		✓ 1)	✓		
	MIFARE Plus S,X	✓ 1)	✓	✓		✓ 1)	✓		
	MIFARE Pro X	✓ 1)	✓	✓		✓ 1)	✓		
	MIFARE Smart MX	✓ 1)	✓	✓		✓ 1)	✓		
	MIFARE Ultralight	✓	✓	✓		✓ 1)	✓		
	MIFARE Ultralight C	✓ 1)	✓	✓		✓ 1)	✓		
	SLE44R35	✓	✓	✓		✓ 1)	✓ 1)		
	SLE66Rxx (my-d move)	✓ 2)	✓ 2)	✓ 2)		✓ 1)	✓ 1)		
	LEGIC Prime					✓	✓		
	LEGIC Advant	✓ 1)	✓ 1)	✓ 1)		✓	✓		
	PayPass	✓ 1)	✓ 2)	✓ 2)		✓ 1)	✓ 1)		
	ISO14443B								
	Calypso		✓ 2)	✓ 2)					
	CEPAS		✓ 2)	✓ 2)					
	Moneo		✓ 2)	✓ 2)					
	Pico Pass		✓ 2)	✓ 2)			✓ 1)		
	SRI512, SRT512		✓	✓					
	SRI4K, SRIX4K		✓	✓					
	ISO18092/ECMA-340								
	Sony FeliCa		✓ 1)	✓ 1)			✓ 1)		
	NFC Forum Tag 1-4		✓	✓			✓ 3)		
	NFC Peer-to-Peer								
	ISO15693								
	EM4x33				✓				
	EM4x35				✓		✓		
	HID iCLASS					✓	✓ 1)		
	HID iCLASS SE/SR					✓	✓ 1)		
	ICODE SLI				✓		✓ 1)	✓	
	M24LR16/64				✓				
	MB89R118/119				✓				
	Tag-it				✓		✓		
SRF55Vxx (my-d vcinity)				✓ 2)		✓			
125 kHz / 134.2kHz	AWID								
	ioProx								
	CASI-RUSCO								
	Cotag								
	EM4100,4102, 4200 ⁶⁾								✓
	EM4150								✓
	EM4305								
	FDX-B								✓
	G-Prox								
	HID DuoProx II (1336)							✓	
	HID ISO Prox II (1386)							✓	
	HID Micro Prox (1391)							✓	
	HID ProxKey III (1346)							✓	
	HID Prox							✓	
	HID Prox II (1326)							✓	
	HITAG 1,2, S								✓
	Indala								
	Keri								
	Miro								✓
	Nexwatch								
	Pyramid								
	Q5								✓
	T5557								✓ 5)
T5567								✓ 5)	
TIRIS/HDX									
TITAN (EM4050)								✓	
UNIQUE								✓	
ZOODIAC								✓	

(()) ELATEC RFID		TWN3		TWN4				
with Antenna →		Casi Rusco	Inditag	Mifare NFC	Mifare NFC P	Mifare NFC PI	Legic NFC	Legic NFC P
without Antenna →				Core Modul	Core Modul	Core Modul	Core Modul	Core Modul
13.56 MHz	ISO14443A							
	MIFARE Classic			✓	✓	✓	✓ 2)	✓ 2)
	MIFARE Mini			✓	✓	✓	✓ 2)	✓ 2)
	MIFARE DESFireEV1			✓	✓	✓	✓	✓
	MIFARE Plus S,X			✓ 2)	✓ 2)	✓ 2)	✓ 2)	✓ 2)
	MIFARE Pro X			✓ 2)	✓ 2)	✓ 2)	✓ 2)	✓ 2)
	MIFARE Smart MX			✓ 2)	✓ 2)	✓ 2)	✓ 2)	✓ 2)
	MIFARE Ultralight			✓	✓	✓	✓	✓
	MIFARE Ultralight C			✓	✓	✓	✓	✓
	SLE44R35			✓	✓	✓	✓ 2)	✓ 2)
	SLE66Rxx (my-d move)			✓ 2)	✓ 2)	✓ 2)	✓ 2)	✓ 2)
	LEGIC Prime						✓	✓
	LEGIC Advant			✓ 1)	✓ 1)	✓ 1)	✓	✓
	PayPass			✓ 2)	✓ 2)	✓ 2)	✓ 2)	✓ 2)
	ISO14443B							
	Calypso			✓ 2)	✓ 2)	✓ 2)		
	CEPAS			✓ 2)	✓ 2)	✓ 2)		
	Moneo			✓ 2)	✓ 2)	✓ 2)		
	Pico Pass			✓ 2)	✓ 2)	✓ 2)	✓ 2)	✓ 2)
	SRI512, SRT512			✓	✓	✓		
	SRI4K, SRX4K			✓	✓	✓		
	ISO18092/ECMA-340							
	Sony FeliCa			✓ 1)	✓ 1)	✓ 1)	✓ 1)	✓ 1)
	NFC Forum Tag 1-4			✓	✓	✓	✓ 3)	✓ 3)
	NFC Peer-to-Peer			✓	✓	✓		
	ISO15693							
	EM4x33			✓ 2)	✓ 2)	✓ 2)		
	EM4x35			✓ 2)	✓ 2)	✓ 2)	✓ 2)	✓ 2)
	HID iCLASS			✓ 1)	✓ 1)	✓	✓ 1)	✓ 1)
	HID iCLASS SE/SR			✓ 1)	✓ 1)	✓ 2)	✓ 1)	✓ 1)
	ICODE SLI			✓	✓	✓	✓	✓
	M24LR16/64			✓	✓	✓	✓	✓
	MB89R118/119							
Tag-it			✓	✓	✓	✓	✓	
SRF55Vxx (my-d vicinity)			✓ 2)	✓ 2)	✓ 2)	✓ 2)	✓ 2)	
125 kHz / 134.2kHz	AWID			✓	✓	✓	✓	✓
	ioProx				✓	✓		✓
	CASI-RUSCO	✓		✓	✓	✓	✓	✓
	Cotag				✓	✓		✓
	EM4100,4102, 4200 ⁶⁾			✓	✓	✓	✓	✓
	EM4150							
	EM4305			✓ 4)	✓ 4)	✓ 4)	✓ 4)	✓ 4)
	FDX-B			✓	✓	✓	✓	✓
	G-Prox				✓	✓		✓
	HID DuoProx II (1336)				✓	✓		✓
	HID ISO Prox II (1386)				✓	✓		✓
	HID Micro Prox (1391)				✓	✓		✓
	HID ProxKey III (1346)				✓	✓		✓
	HID Prox				✓	✓		✓
	HID Prox II (1326)				✓	✓		✓
	HITAG 1,2, S			✓	✓	✓	✓	✓
	Indala		✓		✓	✓		✓
	Keri			✓	✓	✓	✓	✓
	Miro			✓	✓	✓	✓	✓
	Nexwatch				✓	✓		✓
	Pyramid			✓	✓	✓	✓	✓
	Q5							
	T5557			✓	✓	✓	✓	✓
	T5567			✓	✓	✓	✓	✓
	TIRIS/HDX			✓	✓	✓	✓	✓
	TITAN (EM4050)			✓	✓	✓	✓	✓
UNIQUE			✓	✓	✓	✓	✓	
ZODIAC			✓ 4)	✓ 4)	✓ 4)	✓ 4)	✓ 4)	

1) UID only 2) UID Only, read/write depending on demand 3) Only NFC Forum Tag 2-4 4) on request depending on demand 5) only manchester f/64; sequence terminator off 6) Only emulation of 4100,4102

Elatec reserves the right to change any information or data in this document without prior notice. The distribution and the update of this document is not controlled. Elatec declines all responsibility for the use of product with any other specifications but the ones mentioned above. Any additional requirement for a specific customer application has to be validated by the customer himself at his own responsibility.

Where application information is given, it is only advisory and does not form part of the specification. © 2014 Elatec GmbH – DocRev15 – 03/2014